

UFX 7000A Programmable Noise Generator Series

The **UFX7000A** Series instruments contain an amplified noise source that is tuned to provide the best flatness and optimized to deliver an output with a Gaussian amplitude distribution. Noise output power level can be adjusted from 0 to 127 dB in 1 dB (optionally 0.1 dB) steps. The output signal is controlled by an RF type switch. In the standby state, the noise is terminated into an RF load, and in the “on” state it is directed to the output connector.

The UFX7000A Series flexible architecture allows many options to be specified. An internal combiner allows the user to inject an external signal via a front panel connector to add a controlled amount of noise. Noise Com will modify base units for specific customer needs. For pricing and availability, consult the factory.

Optional signal attenuation is available up to 127 dB, in 0.1 or 1 dB steps. A switching filter bank in the noise path allows up to four filters to be connected. The optional filters can be specified in any combination of band pass, low pass, high pass, or notch, with a thru line and 50 Ohm termination (RF load) included. Connectors on the back panel provide a pathway for the external filters to the internal combiner and the front panel instrument output.

General Specifications

- Output White Gaussian noise
- Attenuator 0 to 127 dB in 1 dB steps
- Impedance 50 Ohms
- Typical VSWR 1.5:1
- Standard output SMA female connector (K female for UFX7240)
- Dimensions: 17.22 in. wide x 6.30 in. with feet, high x 19.5 in. deep
- Fold-down feet for bench-top use
- Power 120 VAC, 60 Hz
- Operating temperature: -10° to +65°C

Specifications

UFX7900A Series		Output Characteristics			
Model	Frequency Band	Power	dBm/Hz (dBm)	Flatness (dB)	uV/ root (Hz)
UFX7108	100 Hz - 500 MHz	+10	-77	±1.0	31.6

Options

Option number	Description
U7opt01	N female output connector
U7opt02	BNC female output connector
U7opt03	0 to 127.9 dB noise Attenuator in 0.1 dB steps instead of 127 dB in 1 dB steps
U7opt04	Switch elements, 2 X SP6T for 4 filter paths, 1 thru-path, 1 termination (filters are optional)
U7opt06	75 Ohm output impedance (6 dB loss in the noise path and 12 dB loss in the signal path)
U7opt07	Combiner for input signal (6 dB loss in noise and signal paths)
U7opt08	Double output terminals (switched)
U7opt09	Custom frequency, power, or flatness requirement**
U7opt10	Line power 230 VAC, 50 Hz
U7opt11	RS-232 in addition to standard IEEE-488 interface
U7opt12	0 to 127 dB signal Attenuator in 1 dB steps*
U7opt13	0 to 127.9 dB signal Attenuator in 0.1 dB steps
U7opt14	Ethernet remote control in addition to the standard IEEE-488 interface
U7opt15	Optional 19" rack mounts brackets

* N/A for UFX7218A and UFX7240A (0 to 79.9 for UFX7124A and UFX7126A)

* U7opt07 must also be included when ordering this option, 0 to 79 dB above 2 GHz

** Consult factory for pricing and availability

Applications

- Eb/No, C/N, SNR
- Disk Drive Testing
- BER Testing
- Military Jamming
- GPS Receiver Testing
- CATV Testing
- Spectrum Analyzer Calibration
- Filter Testing
- EMI Testing

NOISE/COM

A WIRELESS TELECOM GROUP COMPANY